

## Powerful technology at the heart of the Enphase system.

Built on the fifth-generation platform, the Enphase S230 Microinverter™ achieves the highest inverter efficiency for module-level power electronics. With its all-AC approach, the S230 simplifies design and installation for 230 VA installations, and delivers optimal energy harvest. The S230 is compatible with storage systems, including battery management systems.

The Enphase S230 integrates seamlessly with the Enphase Envoy-S™ communications gateway, and Enphase Enlighten™ monitoring and analysis software.



### PRODUCTIVE

- Maximizes energy production
- Minimizes impact of shading, dust, and debris

### SIMPLE AND RELIABLE

- No GEC needed for microinverter
- No DC design or string calculation required
- More than 1 million hours of testing
- Industry-leading warranty, up to 25 years

### ADVANCE GRID READY

- Complies with fixed power factor, voltage and frequency ride-through requirements
- Remote updating to respond to changing grid requirements
- Configurable for variable grid profiles like Hawaiian Electric Company (HECO) Rule 14H, California Rule 21



Higher production, best savings



More reliable



Safer AC system



More cost effective

# Technical Specifications



## Enphase S230 Microinverter

INPUT DATA (DC)	S230-60-LL-2-US	
Commonly used module pairings <sup>1</sup>	195 W - 285 W	
Maximum input DC voltage	48 V	
Peak power tracking voltage	27 V - 37 V	
Operating range	16 V - 48 V	
Min/Max start voltage	22 V / 48 V	
Max DC short circuit current	15 A	
OUTPUT DATA (AC)	208 VAC	240 VAC
Peak output power	230 VA	230 VA
Maximum continuous output power	220 VA	220 VA
Nominal voltage/range <sup>2</sup>	208 V / 183-229 V	240 V / 211-264 V
Nominal output current	1.06 A	0.92 A
Nominal frequency/range	60 / 57 - 61 Hz	60 / 57 - 61 Hz
Extended frequency range	57 - 63 Hz	57 - 63 Hz
Power factor at rated power	1.0	1.0
Maximum units per 20 A branch circuit	25 (three phase)	17 (single phase)
Maximum output fault current	663 mA rms, 100 ms	663 mA rms, 100 ms
Power factor (adjustable)	1 / 0.7 leading ... 0.7 lagging	1 / 0.7 leading ... 0.7 lagging
EFFICIENCY	208 VAC	240 VAC
CEC weighted efficiency	96.5 %	97.0 %
Peak inverter efficiency	96.7 %	97.2 %
MECHANICAL DATA		
Ambient temperature range	-40°C to +65°C	
Connector type	MC4-compatible locking	
Dimensions (WxHxD)	172 mm x 175 mm x 35 mm (without bracket)	
Weight	1.8 kg (4 lbs)	
Cooling	Natural convection - No fans	
Enclosure environmental rating	Outdoor - NEMA 6	
FEATURES		
Compatibility	60-cell PV modules	
Communication	Power line	
Integrated ground	The DC circuit meets the requirements for ungrounded PV arrays in NEC 690.35. Equipment ground is provided in the Engage Cable. No additional GEC or ground is required. Ground fault protection (GFP) is integrated into the microinverter.	
Monitoring	Enlighten Manager and MyEnlighten monitoring options	
Compliance	UL1741/IEEE1547, FCC Part 15 Class B, CAN/CSA-C22.2 NO. 0-M91, 0.4-04, and 107.1-01 This product is UL Listed as PV Rapid Shut Down Equipment and conforms with NEC-2014 and NEC-2017 section 690.12 and C22.1-2015 Rule 64-218 Rapid Shutdown of PV Systems, for AC and DC conductors, when installed according manufacturer's instructions.	

1. Suggestion only, inverter self limits DC inputs.
2. Nominal voltage range can be extended beyond nominal if required by the utility.

The specification and key features described in this datasheet may deviate slightly and are not guaranteed. Due to on-going innovation, research and product enhancement, ers (energy rating systems) reserves the right to make any adjustment to the information described herein at any time without notice. Please always obtain the most recent version of the datasheet which shall be duly incorporated into the binding contract made by the parties governing all transactions related to the purchase and sale of the products described herein. Caution: For professional use only. The installation and handling of PV modules requires professional skills and should only be performed by qualified professionals. Please read the safety and installation instructions before using the modules. © Copyright ers (energy rating systems) – April '17 - v1